

vMEyeSuper instructions

1.1 android version

1、Install new mobile monitoring software. The following pic.1 will show on your mobile after installation.





Pic.1 Mobile Monitoring Software

2、Open mobile monitoring software, as follows:








Pic.2 Mobile Monitoring Software Functions







3、: Live view. Click Live view button and you will see pic.3 as below.




Pic.3 Mobile live view interface, the screen can be maximum by Double-click. Also ,your phone can be placed horizontally .

Button functions:


Function key	Name	Function description
	Play	The procedure to start broadcasting a video camera
	Snap pictures	To grasp a picture document appearing in the camera and save it the installed folder.
	Local video	To save the current video documents into default folder.
	Alarm	This light will shine, and alarm information will be on the LED screen when there is motion detection, video loss or video occlusion alarm.
	Setting	Enable user to edit DVR IP address, port, user's name , password setting , the change of equipment alias and watching area shift.

	PTZ	Carry out PTZ control
	Select channel	Enable user to select a certain video of one channel
	PTZ control	Shift between up down left right
	Zoom control	To draw the camera from close to farther distance
	Change focus	Carry out focal length from adding to subtracting
	Aperture changing	Carry out diaphragm from adding to subtracting

4、: Device List. Click the Device List, added devices will be displayed as shown in Pic. 4:



Pic.4 Device List

5、: Add Device. Click it and you will see the following pic.

Back Device Detail Ok

DeviceName:

Address:


TCP Port:


User Name:

Password:

Max Channel:

Pic.5 Add Device

Input device aliases, address, monitoring port (should match with the media port in device network settings), user name, password, and channel numbers. After setting, click  on the top right corner , then device is successfully added.




6、: Edit & modify device information。 Click this button, then click the device you want to modify, the following interface will show up:





The image shows a 'Device Detail' form with a blue header bar containing 'Back' and 'Edit' buttons. The form fields are as follows:

Field	Value
DeviceName:	rzuudd
Address:	1b4b018d6689149a
TCP Port:	34567
User Name:	admin
Password:	
Max Channel	16

Pic.6 Edit & modify device information

Click  on the top right corner, edit the device, click  on the top right corner, click  to the device list。

: Delete device。 Click it, choose the device you want to delete, you will see the following warning:




Pic.7_Deleting device warning

Click OK to delete the device or quit by clicking Cancel.


.6、: Remote Playback。 Click Remote Playback button, you will see the interface

as shown in Pic.8:



Pic.8 Remote Playback

You can choose time, equipment, video channels or video files, click search, the following video document will be on the screen:




Pic.9 Remote Playback Video Documents

Click the document, and click the Remote Playback button, you will see as follows:




Pic.10 Remote Playback

7、: Album。 Click the album button, you can see the snapshot pictures, as the following shows :




Pic.11 Snapshot pic

8、: Local video。 Click the local video, you can view local video files in Pic.12 followed:




Pic.12 Local video

Click on any video file can get local video playback as folloes:



Pic.13 Local Video Playback

- 9、: About。About is a description of the mobile monitoring software, as is shown below:



Pic.14 Description About Monitoring Software

1.2 ios version

1、Install new mobile monitoring software. After installation you will see the following interface.




Pic.1 Mobile monitoring software

2、Open the mobile monitoring software, Pic.2 will be as follows:














Pic.2 Mobile Monitoring Software Functions

- 3、: Live View. Click Live view button and you will see the interface as Pic.3 shows:



Pic.3 Mobile live view interface, the screen can be maximum by Double-click. Also , your phone can be placed horizontally .


Button functions:

Function key	Name	Function description
	Play/pause	Program connect to the device and start / pause the video
	Stop	Stop the video
	Snap pictures	To grasp a picture document appearing in the camera and save it the installed folder.
	Local video	To save the current video documents into default folder.
	Alarm	This light will shine, and alarm information will be on the LED screen when there is motion detection, video loss or video occlusion alarm.
	Setting	Enable users to edit DVR IP address, port, user's name , password setting , the change of equipment alias and watching area shift.
	Select channel	Enable user to select a certain video of one channel
	PTZ control	Shift between up down left right
	Zoom control	To draw the camera from close to farther distance
	Change focus	Carry out focal length from adding to subtracting
	Aperture changing	Carry out diaphragm from adding to subtracting

4、: Device List.Click the Device List,added devices will be displayed in Pic. 4:



Pic. 4 Device List

: Add .Click it and you will see the following pic.

Device Detail

Back Save

Name: Device 01

Address:

TCP Port: 34567


User ID:


Password:

Max Channel: 1 4 8 16 32




Pic.5 Add Device


Input device aliases, address, monitoring port (should match with the media port in device network settings), user name, password, and channel numbers.After setting,

click  on the top right corner , then device is successfully added.

6、 : Edit & modify device information。 Click this button, then click the device you want to modify, the following interface will show up:

Pic.6 Edit & modify device information


Click  on the top right corner, edit the device, click  on the top right corner, click  to the device list.

: Delete device. Click this, choose the device you want to delete, you will see the following warning:



Pic.7_Deleting Device Warning

Click OK to delete the device or quit by clicking Cancel.

5、: Setting. Click setting button, the interface will show as in Pic.8:



Pic.8 Device setting



: Remote Playback. Click Remote Playback button, you will see the interface as shown in Pic.10:



Pic.10 Remote Playback

You can choose time, equipment, video channels or video files, click search, the following video document will be on the screen:

Back


Show

Search Result Count:64

00:00:00-00:05:00	CH1	33.78 M
00:05:00-00:07:58	CH1	20.00 M
00:07:58-00:10:00	CH1	13.80 M
00:10:00-00:15:00	CH1	33.86 M
00:15:00-00:20:00	CH1	33.75 M
00:20:00-00:25:00	CH1	33.80 M
00:25:00-00:30:00	CH1	33.91 M
00:30:00-00:35:00	CH1	33.79 M
00:35:00-00:40:00	CH1	33.84 M

Pic.11 Remote Playback video documents


Click the document, and click the Remote Playback button, you will see as follows:




Pic.12 Remote Playback




: Albums. Click the album button, you can see the snapshot pictures, as the following shows :



Pic.13 Snapshot pictures

6、: Local video。 Click the local video, you can view local video files in Pic.14 followed:




Pic.14 Local video

Click on any video file can get local video playback as folloes:




Pic.15 Local video playback

- 7、: About&Help。 About is a description of this mobile monitoring software, Help is a quick guide to the software, as the following Pic.16 and Pic.17 shows:



Pic.16 Description About Monitoring Software



Pic.17 Quick Guide